

Talentum® 16521

Flameproof (Exd) UV/IR² Flame Detector

The Talentum® Ultra-Violet, dual Infra-Red (UV/IR²) Flame Detector is designed to protect hazardous areas where open fires may be expected and detects almost all flames, including hydrocarbon fires with $4.3\mu m$ emissions through to invisible fires such as hydrogen.

The UV/IR^2 Flame Detector is sensitive to flickering, low frequency (1–15Hz) infra-red radiation emitted by flames during combustion.

This detector has a UV sensor and two IR sensors which respond to different wavelengths of both the ultra-violet and the infra-red spectrum. The signals from these sensors are processed by the detector and checked for characteristics of a flame. The simultaneous detection of both the UV and the IR light by the sensors will signal an alarm. False alarms from flickering sunlight, arc welding and lightning are eliminated by a combination of UV and dual IR signal processing techniques. The Talentum® UV/IR² detector has selectable output options of relay contacts or 4-20mA signal, as standard.

Features

- Highest immunity to false sources
- Solar blind
- Tolerant of fumes, vapours, dust and mist
- Suitable for indoor and outdoor areas
- · Unaffected by convection currents, draughts or wind
- Proven response to multiple fuel types
- Multi-spectrum detection
- Selectable output options
- Selectable response speed
- Selectable sensitivity levels
- Built in auto and manual test
- Low current consumption
- Fast response to fire

Approvals:

ATEX certified:

(L) II 2GD Ex d IIC T6 Gb

[Zones 1, 21, 2 and 22]



Worldwide approvals include EN54:10, with VdS and LPCB certification, as well as SIL 2 rated.

Visit www.ffeuk.com for up to date approvals information.



Applications

- Chemical Plants
- Nuclear Power Sites
- Engine Rooms
- Spray Booths
- Pharmaceutical Production
- Military Applications
- Marine Industry
- Printing

- Refineries
- Fuel Loading Racks
- Storage Tanks
- Aircraft Hangers
- Petrochemical Onshore/Offshore
- Biomass Storage and Handling
- LNG/LPG Production

Accessories

07127 Adjustable Mount Stainless Steel (316) 07279 Weather Shield Stainless Steel (304) 07310 Weather Shield Stainless Steel (316)





Talentum® 16521

Mechanical Specification

-		
Housing Material	Copper Free Aluminium Alloy	
Housing Colour	Red	
Dimensions	150(H) x 146(W) x 137(D) mm	
Weight	2.5kg	
Cable Gland Entries	3 x 20mm	
Wiring	1.0 to 4.0mm ²	

Electrical Specification

Supply Voltage	14 to 30Vdc		
Quiescent Current	8mA, RL2 energised		
	4mA, current loop, RL2 off		
	3mA, RL2 off		
Alarm Current	28mA, RL1 & RL2 energised		
	20mA, current loop, RL1 & 2 off		
	9mA, RL1 energised		
Power Up Time	2 seconds max.		
Test Signal Voltage	14 to 30Vdc		
Relay Outputs	Normally Open or Normally Closed		
- Programmable	Latching or Non-latching		
- Ratings: Current	I.0A Max.		
Voltage	50Vdc Max.		
Power	30W Max.		
	(Note: Resistive Loads Only)		

Environmental

Operating Temperature	-10°C to +55°C
Storage Temperature	-20°C to +65°C
Relative Humidity	95% Non condensing
IP Rating	IP66

Performance

Range - Class I*	0.1 m ² n-heptane at 25m		
- Class 3	0.1 m ² n-heptane at 12m (see EN54:10 for sensitivity settings)		
Field of View	90° min. Cone		
Spectral Response			
- UV	185 to 260nm		
- IR	0.75 to 2.7µm		



FFE Limited 9 Hunting Gate, Hitchin Hertfordshire, SG4 0TJ UK

t +44 (0) 1462 444 740 f +44 (0) 1462 444 789

e sales@ffeuk.com

w www.ffeuk.com

Approvals


_ • •		
CPR	0832-CPR-F0579	
LPCB	1204a/07	
VdS	G212190	
SIL 2	C127_CT003_(2.0)	
ISSeP ATEX	ISSeP03ATEX012X	

Response Characteristics - High Sensitivity

Fuel	Flame Size m (ft)	Distance m (ft)	FFE Factory Tested Distance m(ft)	Average Response time (seconds)
n-Heptane* (Yellow flame)	0.3 × 0.3 (1 × 1)	25 (82)	60 (196)	8
Methylated Spirit* (Clear flame)	0.5 × 0.5 (1.6 × 1.6)	25 (82)	60 (196)	12
Hydrogen (non-visible flame)	0.1 x 0.5 (0.3 x 1.6)	12 (39)	30 (98)	16


^{*} has been tested and approved at Class I

Field of View




To meet the requirements of EN54:10 clause 5.4, where the ratio of the response points. Dmax: Dmin should not exceed 1.41, the horizontal and vertical viewing angles max should not exceed $\pm 30^\circ$.

Flame Detector



Mounting Bracket



Dimensions mm

Installation Recommendations

Please refer to our User Manual for mounting and wiring instructions. The installation of Talentum® flame detectors should be undertaken in accordance with recognised national or international standards and codes of practice.

Specifications and wiring information are provided for information only and are believed to be accurate. FFE Ltd assumes no responsibility for their use. Data and design are subject to change without notice. Installation and wiring instructions are shipped with the products and should always be used for actual installation. For more information, contact your Sales Representative.

Document Part No: 24-0063-04

067

